

# HP CNU Command Line Interface User Guide

## Abstract

This document is intended for the person who configures NIC, FCoE, iSCSI, and NPAR devices.



© Copyright 2014, 2015 Hewlett-Packard Development Company, L.P.

The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

Links to third-party websites take you outside the HP website. HP has no control over and is not responsible for information outside HP.com.

Confidential computer software. Valid license from HP required for possession, use or copying. Consistent with FAR 12.211 and 12.212, Commercial Computer Software, Computer Software Documentation, and Technical Data for Commercial Items are licensed to the U.S. Government under vendor's standard commercial license.

Microsoft®, Windows®, and Windows Server® are trademarks of the Microsoft group of companies.

---

# Contents

- Introduction ..... 4
  - CLI overview ..... 4
  - CLI commands catalog ..... 4
  - Command line syntax ..... 4
- CLI commands ..... 5
  - Common hpcnucli commands ..... 5
  - iSCSI subcommand properties ..... 5
  - Login options ..... 8
  - FCoE subcommand properties ..... 8
  - NPAR subcommand properties ..... 10
  - NIC subcommand properties ..... 10
  - CLI help command screenshot ..... 12
  - CNU system log location ..... 13
- Support and other resources ..... 14
  - Before you contact HP ..... 14
  - HP contact information ..... 14
- Acronyms and abbreviations ..... 15
- Documentation feedback ..... 17

---

# Introduction

## CLI overview

This document provides CLI guidelines for the CNU.

## CLI commands catalog

This document also provides CLI guidelines and usage for the NIC, iSCSI, FCoE, and NPAR subcommands.

## Command line syntax

CLI input is case-insensitive, except when otherwise noted. The general CLI syntax format is as follows:

```
hpcnucli <[command] | [personality]> [<managed element>] [<options>
<parameters>]
```

Item	Description
command	Operation performed
personality	Managed element personality for <code>-ethernet</code> , <code>-iscsi</code> , or <code>-fcoe</code>
managed element	Optional managed element identifier [Ethernet MAC / iSCSI MAC / FCoE Port WWN] This might be required by the personality
options	Commands performed on a managed element
parameters	Optional parameters used for managed element commands

# CLI commands

## Common hpcnucli commands

The common commands for `hpcnucli` are as follows.

Command	Description
<code>hpcnucli -help</code>	Displays general help for the CNU CLI application and a brief synopsis of all commands
<code>hpcnucli -about</code>	Displays information about the product including product name, owner, and version
<code>hpcnucli -showadapter</code>	Displays the adapter name, port name and MAC address, or port WWN, based on iSCSI or FCoE configuration, and for all supported adapters
<code>hpcnucli -import</code>	Imports the XML configuration from one machine to another

## iSCSI subcommand properties

When using the `iSCSI` subcommand, it might be necessary to use login options. For login option information, see "Login options (on page 8)."

The `hpcnucli -iscsi` subcommand options are as follows.

Command	Description
<code>hpcnucli -iscsi -getinitiator</code>	Displays the iSCSI initiator name
<code>hpcnucli -iscsi -setinitiator</code>	Changes the iSCSI initiator name to a specified name Examples: <code>hpcnucli -iscsi -setinitiator &lt;initiator name&gt; [login options]</code> and <code>hpcnucli -iscsi -setinitiator &lt;initiator name&gt; [-mp] [-hd] [-dd] [[-mutualCHAP] &lt;[TargetCHAP] [TargetSecret] [InitiatorCHAP] [InitiatorSecret]&gt;]</code> and <code>hpcnucli -iscsi -setinitiator &lt;initiator name&gt; [-mp] [-hd] [-dd] [[-oneWayCHAP] &lt;[TargetCHAP] [InitiatorCHAP]&gt;]</code>
<code>hpcnucli -iscsi -isns -listall</code>	Lists all iSNS servers
<code>hpcnucli -iscsi -isns -add</code>	Adds an iSNS server to the system based on a server IP address that is entered as an argument Example: <code>hpcnucli -iscsi -isns -add &lt;IP address&gt;</code>
<code>hpcnucli -iscsi -isns -remove</code>	Removes an iSNS server to the system based on a server IP address that is entered as an argument Example: <code>hpcnucli -iscsi -isns -remove &lt;IP address&gt;</code>

Command	Description
<code>hpcnucli -iscsi -portinfo</code>	Displays all information that is related to a specified port on the console Example: <code>hpcnucli -iscsi &lt;MAC address&gt; -portinfo</code>
<code>hpcnucli -iscsi -portstat</code>	Displays all port statistics for a specified port Example: <code>hpcnucli -iscsi &lt;MAC address&gt; -portstat</code>
<code>hpcnucli -iscsi -defparam</code>	Displays the default driver parameter that is related to the port on the console Example: <code>hpcnucli -iscsi &lt;MAC address&gt; -defparam</code>
<code>hpcnucli -iscsi -getbootconfig</code>	Displays the current boot configuration for the port on the console Example: <code>hpcnucli -iscsi &lt;MAC address&gt; -getbootconfig</code>
<code>hpcnucli -iscsi -setbootconfig</code>	Displays the current boot configuration for the port on the console and enables you to modify the boot configuration interactively Example: <code>hpcnucli -iscsi &lt;MAC address&gt; -setbootconfig</code>
<code>hpcnucli -iscsi -portal -listall</code>	Displays all portals that are in use Example: <code>hpcnucli -iscsi &lt;MAC address&gt; -portal -listall</code>
<code>hpcnucli -iscsi -portal -add</code>	Adds a portal to the system based on a target IP address and port number that is entered as an argument Login options are optional Example: <code>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -portal -add &lt;portal IP of target iSCSI target portal&gt; [port number] [login option]</code>
<code>hpcnucli -iscsi -portal -remove</code>	Removes a portal from the system based on a target IP address and port number that is entered as an argument The default iSCSI target portal port is 3260 Login options are optional Example: <code>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -portal -remove &lt;portal IP of target iSCSI target portal&gt; [port number] [login option]</code>
<code>hpcnucli -iscsi -target -listall</code>	Displays all currently discovered targets Example: <code>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -target -listall</code>
<code>hpcnucli -iscsi -target -listactive</code>	Displays all currently connected targets Example: <code>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -target -listactive</code>

Command	Description
<code>hpcnucli -iscsi -target -login</code>	<p>Adds a target to the system based on an iSCSI target IQN, portal IP address, and port number that is entered as an argument</p> <p>Login options are optional</p> <p>Example:</p> <pre>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -target -login &lt;iSCSI target you want to add and log into&gt; &lt;IP address for the iSCSI target portal&gt; [port number for iSCSI target portal] [login option]</pre>
<code>hpcnucli -iscsi -target -getinfo</code>	<p>Retrieves information for a specified target</p> <p>Example:</p> <pre>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -target -getinfo &lt;iSCSI target IQN&gt;</pre>
<code>hpcnucli -iscsi -target -sessioninfo</code>	<p>Retrieves information for the currently logged-in session</p> <p>The session ID ranges from 0 to N-1, where N is the session count</p> <p>The default value for the session ID is 0</p> <p>Example:</p> <pre>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -target -sessioninfo &lt;iSCSI target IQN&gt; [session ID]</pre>
<code>hpcnucli -iscsi -target -logout</code>	<p>Logs-out of a defined target</p> <p>The default value for the session ID is 0</p> <p>Example:</p> <pre>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -target -logout &lt;iSCSI target IQN&gt; [Session ID]</pre>
<code>hpcnucli -iscsi -target -remove</code>	<p>Removes a target from the system based on an iSCSI target IQN that is entered as an argument</p> <p>Example:</p> <pre>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -target -remove &lt;iSCSI target IQN&gt;</pre>
<code>hpcnucli -iscsi -target -lunlist</code>	<p>Displays all active LUNs</p> <p>Example:</p> <pre>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -target -lunlist &lt;iSCSI target IQN&gt;</pre>
<code>hpcnucli -iscsi -ping</code>	<p>Verifies connectivity by sending an ICMP ping request to a specified IP address</p> <p>Example:</p> <pre>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -ping &lt;IP address you are sending the ping request&gt;</pre>
<code>hpcnucli -iscsi -modifytcpip -ipv4/ipv6 -dhcp</code>	<p>Sets an iSCSI host (either IPv4 or IPv6) as a DHCP client so that its TCP/IP settings are automatically configured by a DHCP server; the VLAN ID range is from 0 - 4094, where 0 represents VLAN disable.</p> <p>Example:</p> <pre>hpcnucli -iscsi &lt;MAC address&gt; -modifytcpip -ipv4/ipv6 -dhcp [optional VLAN ID]</pre>

Command	Description
<code>hpcnucli -iscsi -modifytcpip ipv4/ipv6 -static</code>	Sets the TCP/IP settings on an iSCSI host (either IPv4 or IPv6) to be configured manually; the VLAN ID range is from 0-4094, where 0 represents VLAN disable. Example: <code>hpcnucli -iscsi &lt;MAC address on iSCSI host port&gt; -modifytcpip -ipv4/ipv6 -static &lt;VLAN ID&gt; &lt;IP address&gt; &lt;subnet mask&gt; &lt;gateway&gt;</code>

## Login options

The `hpcnucli -iscsi` login options are as follows.

Login option	Description
<code>-mp</code>	Multi-path, enabled by default
<code>-hd</code>	Header digest
<code>-dd</code>	Data digest
<code>-option</code>	Specified CHAP values, either mutual or one-way Possible CHAP values: <ul style="list-style-type: none"> <li>• <code>[-Option (-mutualCHAP   -oneWayCHAP)]</code></li> <li>• <code>[TargetCHAP]</code></li> <li>• <code>[TargetSecret]</code></li> <li>• <code>[InitiatorCHAP]</code></li> <li>• <code>[InitiatorSecret]</code></li> </ul>

## FCoE subcommand properties

The `hpcnucli -fcoe` subcommand options are as follows.

Command	Description
<code>hpcnucli -fcoe -portinfo</code>	Displays all the information related to an FCoE port that you specify Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -portinfo</code>
<code>hpcnucli -fcoe -resetstat</code>	Resets FCoE port statistic attribute values to 0 Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -resetstat</code>
<code>hpcnucli -fcoe -getdcbinfo</code>	Displays negotiated DCB information for a portWWN you specify Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -getdcbinfo</code>
<code>hpcnucli -fcoe -getdcbconfig</code>	Displays the current DCB admin configuration for a portWWN you specify Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -getdcbconfig</code>



Command	Description
<code>hpcnucli -fcoe -setdcb</code>	Modifies the DCB admin configuration interactively Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -setdcb</code>
<code>hpcnucli -fcoe -target -listactive</code>	Displays the list of all the active targets connected to a port you specify Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -target -listactive</code>
<code>hpcnucli -fcoe -target -pbindinfo</code>	Displays the list of all persistent targets connected to a port you specify Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -target -pbindinfo</code>
<code>hpcnucli -fcoe -target -getinfo</code>	Displays information for a target you specify Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -target -getinfo &lt;portWWN of the connected target&gt;</code>
<code>hpcnucli -fcoe -target -lunlist</code>	Displays the list of the LUNs associated with a target you specify Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -target -lunlist &lt;portWWN of the connected target&gt;</code>
<code>hpcnucli -fcoe -getbootconfig</code>	Displays FCoE boot configuration for a port you specify Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -getbootconfig</code>
<code>hpcnucli -fcoe -setbootconfig</code>	Displays the current boot configuration for the port on the console and allows you to set the boot configuration interactively Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -setbootconfig</code>
<code>hpcnucli -fcoe -ping</code>	Verifies connectivity by sending a SCSI inquiry command request to a portWWN you specify The optional parameters are as follows: <ul style="list-style-type: none"> <li>• <code>pcount</code> is the number of packets sent in the ping</li> <li>• <code>timeout</code> is the maximum time to wait for receiving a packet</li> </ul> Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -ping &lt;portWWN of the connected target&gt; [-pcount] [-timeout]</code>
<code>hpcnucli -fcoe -getfip</code>	Displays FIP for a port you specify Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -getfip</code>
<code>hpcnucli -fcoe -setfip</code>	Set the VLAN ID for the FIP of a specific port. The VLAN ID range is 0~4094, where 0 represents VLAN disable. Example: <code>hpcnucli -fcoe &lt;portWWN of the FCoE adapter&gt; -setfip &lt;VLAN ID&gt;</code>

## NPAR subcommand properties

The `hpcnucli -npar` subcommand options are as follows.

Command	Description
<code>hpcnucli -npar -get</code>	Displays NPAR information related to a specified port on the console (only in NPAR mode). If the current mode is SF, the CLI displays the message, Current mode is SF. Example: <code>hpcnucli -npar &lt;MAC&gt; -get</code>
<code>hpcnucli -npar -set</code>	Displays the current mode for the port on the console and enables interactive setting. The parameters are as follows: SF: Port flow control NPAR: Port flow control, Physical function, Bandwidth weight (0 - 100), and max bandwidth (0 - 100) Requires rebooting the system after setting Example: <code>hpcnucli -npar &lt;MAC&gt; -set</code>
<code>hpcnucli -res -get</code>	Displays the storage personality that is related to a specified port on the console (only in SF mode). If the current mode is NPAR, the CLI displays the message, This command is only effective for SF mode. Example: <code>hpcnucli -res &lt;MAC&gt; -get</code> (-res indicates "resource allocation")
<code>hpcnucli -res -set</code>	Displays storage personality for the port on the console and enables the interactive setting of the storage personality (only in SF mode). If the current mode is NPAR, the CLI displays the message, This command is only effective for SF mode. Requires rebooting the system after setting Example: <code>hpcnucli -res &lt;MAC&gt; -set</code> (-res indicates "resource allocation")

## NIC subcommand properties

The `hpcnucli -ethernet` subcommand options are as follows.

Command	Description
<code>hpcnucli -ethernet -portinfo</code>	Displays all information related to a specified port on the console. Example: <code>hpcnucli -ethernet &lt;MAC address&gt; -portinfo</code>
<code>hpcnucli -ethernet -portstat</code>	Displays all port statistics for a specified port. Example: <code>hpcnucli -ethernet &lt;MAC address&gt; -portstat</code>
<code>hpcnucli -ethernet -resetstat</code>	Resets Ethernet port statistic attribute values to 0. Example: <code>hpcnucli -ethernet &lt;MAC address&gt; -resetstat</code>

Command	Description
<code>hpcnucli -ethernet -getadapinfo</code>	Displays all information related to an Ethernet port on the console. Example: <code>hpcnucli -ethernet &lt;MAC&gt; -getadapinfo</code>
<code>hpcnucli -ethernet -setadapinfo</code>	Displays all information related to an Ethernet port on the console and allows you to modify the settings interactively. Example: <code>hpcnucli -ethernet &lt;MAC&gt; -setadapinfo</code>
<code>hpcnucli -ethernet -modifytcpip -ipv4/ipv6 -dhcp</code>	Sets an Ethernet host (either IPv4 or IPv6) as a DHCP client so that its TCP/IP settings are automatically configured by a DHCP server; the VLAN ID range is from 0-4094, where 0 represents VLAN disable. Example: <code>hpcnucli -ethernet &lt;MAC&gt; -modifytcpip -ipv4/ipv6 -dhcp [optional VLAN ID]</code>
<code>hpcnucli -ethernet -modifytcpip -ipv4/ipv6 -static</code>	Sets the TCP/IP settings on an Ethernet host (either IPv4 or IPv6) to be configured manually; the VLAN ID range is from 0-4094, where 0 represents VLAN disable. Example: <code>hpcnucli -ethernet &lt;MAC address&gt; -modifytcpip -ipv4/ipv6 -static &lt;VLAN ID&gt; &lt;IP address&gt; &lt;subnet mask&gt; &lt;gateway&gt;</code>

# CLI help command screenshot

The following is a screenshot of the CLI help command output.

```
C:\Program Files\HP Converged Network Utility>hpcnucli -help
Hewlett Packard Enterprise Converged Network Utility CLI(5.0.4.1)
(C) Copyright 2015 Hewlett Packard Enterprise Development LP

List of supported commands for HPCNUCLI
<..> Mandatory Arguments
[...> Optional Arguments

hpcnucli -about
hpcnucli -showadapter
hpcnucli -import
        -iscsi -getinitiator
        -iscsi -setinitiator <Initiator Name> [*login options]
        -isns -listall
                -add <iSNS Server IP>
                -remove <iSNS Server IP>
        -iscsi <MAC>
                -portinfo
                -portstat
                -defparam
                -getbootconfig
                -setbootconfig
                -portal -listall
                        -add <Portal IP> <Port Number***> [*login option]
                        -remove <Portal IP> <Port Number***>
                -target
                        -listall
                        -listactive
                        -login <Target Name> <IP> <Port Number***> [*login
option]
                        -getinfo <Target Name>
                        -sessioninfo <Target Name> <Session ID>
                        -logout <Target Name> <Session ID>
                        -remove <Target Name>
                        -lunlist <Target Name>
                -ping <IP Address>
                -modifytcPIP -dhcp [VLAN ID***]
                        -static <VLAN ID> <IP Address> <Subnet Mask>

<Gateway>
        -fcoe <portWWN> -portinfo
        -fcoe <portWWN> -portstat
        -fcoe <portWWN> -resetstat
        -fcoe <portWWN> -getdcbinfo
        -fcoe <portWWN> -getdcbconfig
        -fcoe <portWWN> -setdcb
        -fcoe <portWWN> -target -listactive
                                -pbinding
                                -getinfo <Target Name>
                                -lunlist <Target Name>
                                -getbootconfig
                                -setbootconfig
                                -ping <Target Name>
                                -ping <Target Name> -pcount <Count>
                                -ping <Target Name> -timeout <time in secs>

        -npar <MAC> -get
        -npar <MAC> -set
        -res <MAC> -get
        -res <MAC> -set
        -ethernet <MAC> -portinfo
        -ethernet <MAC> -portstat
        -ethernet <MAC> -resetstat
        -ethernet <MAC> -getadapinfo
        -ethernet <MAC> -setadapinfo
        -ethernet <MAC> -gettcPIP
        -ethernet <MAC> -modifytcPIP -ipv4 -dhcp [VLAN ID***]
                                    -ipv6 -dhcp [VLAN ID***]
                                    -ipv4 -static <VLAN ID> <IP Address> <Subn
et Mask> <Gateway>
                                    -ipv6 -static <VLAN ID> <IP Address> <Pref
ix Length> [Gateway]

x <-mp> <-hd> <-dd> <-Option (-mutualCHAP | -oneWayCHAP)> <TargetCHAP> <Target
Secret> <InitiatorCHAP> <InitiatorSecret>
** Default Port Number : 3260
*** Default VLAN ID : 1
```

# CNU system log location

The CNU system log is stored in the following directory:

```
$installdir$\hpcnu.log
```

---

# Support and other resources

## Before you contact HP

Be sure to have the following information available before you call HP:

- Active Health System log (HP ProLiant Gen8 or later products)  
Download and have available an Active Health System log for 7 days before the failure was detected. For more information, see the *HP iLO 4 User Guide* or *HP Intelligent Provisioning User Guide* on the HP website (<http://www.hp.com/go/ilo/docs>).
- Onboard Administrator SHOW ALL report (for HP BladeSystem products only)  
For more information on obtaining the Onboard Administrator SHOW ALL report, see the HP website (<http://www.hp.com/go/OAlog>).
- Technical support registration number (if applicable)
- Product serial number
- Product model name and number
- Product identification number
- Applicable error messages
- Add-on boards or hardware
- Third-party hardware or software
- Operating system type and revision level

## HP contact information

For United States and worldwide contact information, see the Contact HP website (<http://www.hp.com/go/assistance>).

In the United States:

- To contact HP by phone, call 1-800-334-5144. For continuous quality improvement, calls may be recorded or monitored.
- If you have purchased a Care Pack (service upgrade), see the Support & Drivers website (<http://www8.hp.com/us/en/support-drivers.html>). If the problem cannot be resolved at the website, call 1-800-633-3600. For more information about Care Packs, see the HP website (<http://pro-aq-sama.houston.hp.com/services/cache/10950-0-0-225-121.html>).

---

# Acronyms and abbreviations

## CHAP

Challenge Handshake Authentication Protocol

## CNU

Converged Network Utility

## DHCP

Dynamic Host Configuration Protocol

## FCoE

Fibre Channel over Ethernet

## ICMP

Internet Control Message Protocol

## IQN

iSCSI qualified name

## iSCSI

Internet Small Computer System Interface

## iSNS

Internet Storage Name Service

## LUN

logical unit number

## MAC

Media Access Control

## NPAR

NIC partitioning

## SF

single function

VLAN

virtual local-area network

WWN

World Wide Name



---

# Documentation feedback

HP is committed to providing documentation that meets your needs. To help us improve the documentation, send any errors, suggestions, or comments to Documentation Feedback (<mailto:docsfeedback@hp.com>). Include the document title and part number, version number, or the URL when submitting your feedback.