

X Synchronization Extension Library

Version 3.0

X Consortium Standard

X Version 11, Release 6.9/7.0

Tim Glauert

thg@cam-orl.co.uk

Olivetti Research / MultiWorks

Dave Carver

dcc@athena.mit.edu

**Digital Equipment Corporation,
MIT / Project Athena**

Jim Gettys

jg@crl.dec.com

**Digital Equipment Corporation,
Cambridge Research Laboratory**

David P. Wiggins

dpw@x.org

X Consortium, Inc.

Copyright 1991 by Olivetti Research Limited, Cambridge, England and Digital Equipment Corporation, Maynard, Massachusetts.

Permission to use, copy, modify, and distribute this documentation for any purpose and without fee is hereby granted, provided that the above copyright notice appear in all copies. Olivetti, Digital, MIT, and the X Consortium make no representations about the suitability for any purpose of the information in this document. This documentation is provided as is without express or implied warranty.

Copyright (c) 1991 X Consortium, Inc.

Permission is hereby granted, free of charge, to any person obtaining a copy of this software and associated documentation files (the "Software"), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:

The above copyright notice and this permission notice shall be included in all copies or substantial portions of the Software.

THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE

WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT. IN NO EVENT SHALL THE X CONSORTIUM BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

Except as contained in this notice, the name of the X Consortium shall not be used in advertising or otherwise to promote the sale, use or other dealings in this Software without prior written authorization from the X Consortium.

1 Synchronization Protocol

The core X protocol makes no guarantees about the relative order of execution of requests for different clients. This means that any synchronization between clients must be done at the client level in an operating system-dependent and network-dependent manner. Even if there was an accepted standard for such synchronization, the use of a network introduces unpredictable delays between the synchronization of the clients and the delivery of the resulting requests to the X server.

The core X protocol also makes no guarantees about the time at which requests are executed, which means that all clients with real-time constraints must implement their timing on the host computer. Any such timings are subject to error introduced by delays within the operating system and network and are inefficient because of the need for round-trip requests that keep the client and server synchronized.

The synchronization extension provides primitives that allow synchronization between clients to take place entirely within the X server. This removes any error introduced by the network and makes it possible to synchronize clients on different hosts running different operating systems. This is important for multimedia applications, where audio, video, and graphics data streams are being synchronized. The extension also provides internal timers within the X server to which client requests can be synchronized. This allows simple animation applications to be implemented without any round-trip requests and makes best use of buffering within the client, network, and server.

1.1 Description

The mechanism used by this extension for synchronization within the X server is to block the processing of requests from a client until a specific synchronization condition occurs. When the condition occurs, the client is released and processing of requests continues. Multiple clients may block on the same condition to give inter-client synchronization. Alternatively, a single client may block on a condition such as an animation frame marker.

The extension adds **Counter** and **Alarm** to the set of resources managed by the server. A counter has a 64-bit integer value that may be increased or decreased by client requests or by the server internally. A client can block by sending an **Await** request that waits until one of a set of synchronization conditions, called TRIGGERS, becomes TRUE.

The **CreateCounter** request allows a client to create a **Counter** that can be changed by explicit **SetCounter** and **ChangeCounter** requests. These can

be used to implement synchronization between different clients.

There are some counters, called **System Counters**, that are changed by the server internally rather than by client requests. The effect of any change to a system counter is not visible until the server has finished processing the current request. In other words, system counters are apparently updated in the gaps between the execution of requests rather than during the actual execution of a request. The extension provides a system counter that advances with the server time as defined by the core protocol, and it may also provide counters that advance with the real-world time or that change each time the CRT screen is refreshed. Other extensions may provide their own extension-specific system counters.

The extension provides an **Alarm** mechanism that allows clients to receive an event on a regular basis when a particular counter is changed.

2 C Language Binding

The C routines provide direct access to the protocol and add no additional semantics.

The include file for this extension is `<X11/extensions/sync.h>`.

Most of the names in the language binding are derived from the protocol names by prepending **XSync** to the protocol name and changing the capitalization.

2.1 C Functions

Most of the following functions generate SYNC protocol requests.

Status

```
XSyncQueryExtension ( Display * dpy, int * event_base_return,
                     int * error_base_return )
```

If dpy supports the SYNC extension, **XSyncQueryExtension** returns **True**, sets **event_base_return* to the event number for the first SYNC event, and sets **error_base_return* to the error number for the first SYNC error. If dpy does not support the SYNC extension, it returns **False**.

Status

```
XSyncInitialize ( Display * dpy, int * major_version_return,
                 int * minor_version_return )
```

XSyncInitialize sets **major_version_return* and **minor_version_return* to the major/minor SYNC protocol version supported by the server. If the XSync library is compatible with the version returned by the server, this function returns **True**. If dpy does not support the SYNC extension, or if there was an error during communication with the server, or if the server and library protocol versions are incompatible, this function returns **False**. The only XSync function that may be called before this function is **XSyncQueryExtension**. If a client violates this rule, the effects of all XSync calls that it makes are undefined.

XSyncSystemCounter *

XSyncListSystemCounters (Display * *dpy*, int * *n_counters_return*)

XSyncListSystemCounters returns a pointer to an array of system counters supported by the display and sets **n_counters_return* to the number of counters in the array. The array should be freed with **XSyncFreeSystemCounterList**. If dpy does not support the SYNC extension, or if there was an error during communication with the server, or if the server does not support any system counters, this function returns NULL.

XSyncSystemCounter has the following fields:

```
char *          name;          /* null-terminated name of system counter */
XSyncCounter    counter;       /* counter id of this system counter */
XSyncValue      resolution;    /* resolution of this system counter */
```

void

XSyncFreeSystemCounterList (XSyncSystemCounter * *list*)

XSyncFreeSystemCounterList frees the memory associated with the system counter list returned by **XSyncListSystemCounters**.

XSyncCounter

XSyncCreateCounter (Display * *dpy*, XSyncValue *initial_value*)

XSyncCreateCounter creates a counter on the dpy with the given *initial_value* and returns the counter ID. It returns **None** if dpy does not support the SYNC extension.

Status

XSyncSetCounter (Display * *dpy*, XSyncCounter *counter*, XSyncValue *value*)

XSyncSetCounter sets counter to value. It returns **False** if dpy does not support the SYNC extension; otherwise, it returns **True**.

Status

XSyncChangeCounter (Display * *dpy*, XSyncCounter *counter*,
XSyncValue *value*)

XSyncChangeCounter adds value to counter. It returns **False** if dpy does not support the SYNC extension; otherwise, it returns **True**.

Status

XSyncDestroyCounter (Display * *dpy*, XSyncCounter *counter*)

XSyncDestroyCounter destroys counter. It returns **False** if dpy does not support the SYNC extension; otherwise, it returns **True**.

Status

XSyncQueryCounter (Display * *dpy*, XSyncCounter *counter*,
XSyncValue * *value_return*)

XSyncQueryCounter sets **value_return* to the current value of counter. It returns **False** if there was an error during communication with the server or if dpy does not support the SYNC extension; otherwise, it returns **True**.

Status

XSyncAwait (Display * *dpy*, XSyncWaitCondition * *wait_list*,
int *n_conditions*)

XSyncAwait awaits on the conditions in *wait_list*. The *n_conditions* is the number of wait conditions in *wait_list*. It returns **False** if dpy does not support the SYNC extension; otherwise, it returns **True**. The await is processed asynchronously by the server; this function always returns immediately after issuing the request.

XSyncWaitCondition has the following fields:

XSyncCounter	trigger.counter;	/* counter to trigger on */
XSyncValueType	trigger.value_type;	/* absolute/relative */
XSyncValue	trigger.wait_value;	/* value to compare counter to */
XSyncTestType	trigger.test_type;	/* pos/neg comparison/transition */
XSyncValue	event.threshold;	/* send event if past threshold */

XSyncValueType can be either **XSyncAbsolute** or **XSyncRelative**.

XSyncTestType can be one of **XSyncPositiveTransition**,
XSyncNegativeTransition, **XSyncPositiveComparison**, or
XSyncNegativeComparison.

XSyncAlarm

XSyncCreateAlarm (Display * *dpy*, unsigned long *values_mask*,
XSyncAlarmAttributes * *values*)

XSyncCreateAlarm creates an alarm and returns the alarm ID. It returns **None** if the display does not support the SYNC extension. The *values_mask* and *values* specify the alarm attributes.

XSyncAlarmAttributes has the following fields. The `attribute_mask` column specifies the symbol that the caller should OR into `values_mask` to indicate that the value for the corresponding attribute was actually supplied. Default values are used for all attributes that do not have their `attribute_mask` OR'ed into `values_mask`. See the protocol description for **CreateAlarm** for the defaults.

type	field name	attribute_mask
XSyncCounter	trigger.counter;	XSyncCACounter
XSyncValueType	trigger.value_type;	XSyncCAValueType
XSyncValue	trigger.wait_value;	XSyncCAValue
XSyncTestType	trigger.test_type;	XSyncCATestType
XSyncValue	delta;	XSyncCADelta
Bool	events;	XSyncCAEvents
XSyncAlarmState	state;	client cannot set this

Status

XSyncDestroyAlarm (Display * *dpy*, XSyncAlarm *alarm*)

XSyncDestroyAlarm destroys alarm. It returns **False** if *dpy* does not support the SYNC extension; otherwise, it returns **True**.

Status

XSyncQueryAlarm (Display * *dpy*, XSyncAlarm *alarm*,
XSyncAlarmAttributes * *values_return*)

XSyncQueryAlarm sets **values_return* to the alarm's attributes. It returns **False** if there was an error during communication with the server or if *dpy* does not support the SYNC extension; otherwise, it returns **True**.

Status

XSyncChangeAlarm (Display * *dpy*, XSyncAlarm *alarm*,
unsigned long *values_mask*, XSyncAlarmAttributes * *values*)

XSyncChangeAlarm changes alarm's attributes. The attributes to change are specified as in **XSyncCreateAlarm**. It returns **False** if *dpy* does not support the SYNC extension; otherwise, it returns **True**.

Status

XSyncSetPriority (Display * *dpy*, XID *client_resource_id*, int *priority*)

XSyncSetPriority sets the priority of the client owning *client_resource_id* to *priority*. If *client_resource_id* is **None**, it sets the caller's priority. It returns **False** if *dpy* does not support the SYNC extension; otherwise, it returns **True**.

Status

XSyncGetPriority (Display * *dpy*, XID *client_resource_id*,
int * *return_priority*)

XSyncGetPriority sets **return_priority* to the priority of the client owning *client_resource_id*. If *client_resource_id* is **None**, it sets **return_priority* to the caller's priority. It returns **False** if there was an error during communication with the server or if dpy does not support the SYNC extension; otherwise, it returns **True**.

2.2 C Macros/Functions

The following procedures manipulate 64-bit values. They are defined both as macros and as functions. By default, the macro form is used. To use the function form, *#undef* the macro name to uncover the function.

void

XSyncIntToValue (XSyncValue **pv*, int *i*)

Converts *i* to an **XSyncValue** and stores it in **pv*. Performs sign extension (**pv* will have the same sign as *i*.)

void

XSyncIntsToValue (XSyncValue **pv*, unsigned int *low*, int *high*)

Stores *low* in the low 32 bits of **pv* and *high* in the high 32 bits of **pv*.

Bool

XSyncValueGreaterThan (XSyncValue *a*, XSyncValue *b*)

Returns **True** if *a* is greater than *b*, else returns **False**.

Bool

XSyncValueLessThan (XSyncValue *a*, XSyncValue *b*)

Returns **True** if *a* is less than *b*, else returns **False**.

Bool

XSyncValueGreaterOrEqual (XSyncValue *a*, XSyncValue *b*)

Returns **True** if *a* is greater than or equal to *b*, else returns **False**.

Bool

XSyncValueLessOrEqual (XSyncValue *a*, XSyncValue *b*)

Returns **True** if *a* is less than or equal to *b*.

Bool

XSyncValueEqual (XSyncValue *a*, XSyncValue *b*)

Returns **True** if *a* is equal to *b*, else returns **False**.

Bool

XSyncValueIsNegative (XSyncValue *v*)

Returns **True** if *v* is negative, else returns **False**.

Bool

XSyncValueIsZero (XSyncValue *v*)

Returns **True** if *v* is zero, else returns **False**.

Bool

XSyncValueIsPositive (XSyncValue *v*)

Returns **True** if *v* is positive, else returns **False**.

unsigned int

XSyncValueLow32 (XSyncValue *v*)

Returns the low 32 bits of *v*.

int

XSyncValueHigh32 (XSyncValue *v*)

Returns the high 32 bits of *v*.

void

XSyncValueAdd (XSyncValue * *presult*, XSyncValue *a*, XSyncValue *b*,
Bool * *poverflow*)

Adds *a* to *b* and stores the result in **presult*. If the result could not fit in 64 bits, **poverflow* is set to **True**, else it is set to **False**.

void

XSyncValueSubtract (XSyncValue * *presult*, XSyncValue *a*, XSyncValue *b*,
Bool * *poverflow*)

Subtracts *b* from *a* and stores the result in **presult*. If the result could not fit in 64 bits, overflow is set to **True**, else it is set to **False**.

void

XSyncMaxValue (XSyncValue * *pv*)

Sets **pv* to the maximum value expressible in 64 bits.

void

XSyncMinValue (XSyncValue * *pv*)

Sets **pv* to the minimum value expressible in 64 bits.

2.3 Events

Let *event_base* be the value *event_base_return* as defined in the function XSyncQueryExtension.

An `XSyncCounterNotifyEvent`'s type field has the value `event_base + XSyncCounterNotify`. The fields of this structure are:

```

int          type;          /* event base + XSyncCounterNotify */
unsigned long serial;       /* number of last request processed by server */
Bool         send_event;    /* true if this came from a SendEvent request */
Display *    display;       /* Display the event was read from */
XSyncCounter counter;       /* counter involved in await */
XSyncValue   wait_value;    /* value being waited for */
XSyncValue   counter_value; /* counter value when this event was sent */
Time         time;          /* milliseconds */
int          count;         /* how many more events to come */
Bool         destroyed;     /* True if counter was destroyed */

```

An `XSyncAlarmNotifyEvent`'s type field has the value `event_base + XSyncAlarmNotify`. The fields of this structure are:

```

int          type;          /* event base + XSyncAlarmNotify */
unsigned long serial;       /* number of last request processed by server */
Bool         send_event;    /* true if this came from a SendEvent request */
Display *    display;       /* Display the event was read from */
XSyncAlarm   alarm;         /* alarm that triggered */
XSyncValue   counter_value; /* value that triggered the alarm */
XSyncValue   alarm_value;   /* test value of trigger in alarm */
Time         time;          /* milliseconds */
XSyncAlarmState state;      /* new state of alarm */

```

2.4 Errors

Let `error_base` be the value `error_base_return` as defined in the function `XSyncQueryExtension`.

An `XSyncAlarmError`'s `error_code` field has the value `error_base + XSyncBadAlarm`. The fields of this structure are:

```

int          type;
Display *    display;       /* Display the event was read from */
XSyncAlarm   alarm;         /* resource id */
unsigned long serial;       /* serial number of failed request */
unsigned char error_code;    /* error base + XSyncBadAlarm */
unsigned char request_code;  /* Major op-code of failed request */
unsigned char minor_code;    /* Minor op-code of failed request */

```

An `XSyncCounterError`'s `error_code` field has the value `error_base + XSyncBadCounter`. The fields of this structure are:

```

int          type;
Display *    display;      /* Display the event was read from */
XSyncCounter counter;      /* resource id */
unsigned long serial;      /* serial number of failed request */
unsigned char error_code;   /* error base + XSyncBadCounter */
unsigned char request_code; /* Major op-code of failed request */
unsigned char minor_code;   /* Minor op-code of failed request */

```